

G05BAFP

NAG Parallel Library Routine Document

Note: before using this routine, please read the Users' Note for your implementation to check for implementation-dependent details. You are advised to enclose any calls to NAG Parallel Library routines between calls to Z01AAFP and Z01ABFP.

1 Description

The routine G05BAFP generates a vector of pseudo-random numbers of length n from a uniform distribution in the open interval (0,1).

A total of 273 statistically independent generators are available; it is possible to select a particular generator and initialize the seeds for the generator by a preceding call to G05BBFP. If G05BBFP is not used, default values for the generator and the seeds are assumed.

2 Specification

```
SUBROUTINE G05BAFP(N, X)
  INTEGER          N
  DOUBLE PRECISION X(*)
```

3 Usage

3.1 Definitions

None.

3.2 Global and Local Arguments

All arguments are local.

4 Arguments

- 1:** N — INTEGER *Local Input/Local Output*
On entry: n , the number of pseudo-random numbers to be generated. If $N < 1$, no pseudo-random numbers are generated.
On exit: the actual number of pseudo-random numbers which were generated.
- 2:** X(*) — DOUBLE PRECISION array *Local Output*
On exit: the n pseudo-random numbers from the specified uniform distribution.

5 Errors and Warnings

None.

6 Further Comments

Repeatable sequences of random numbers can be generated by calling G05BBFP to set the seeds and generator number before calling G05BAFP.

G05BAFP may be called without a prior call to Z01AAFP.

6.1 Algorithmic Detail

Each basic generator uses a Wichmann–Hill type generator (Wichmann and Hill [3]), which is a variant of a multiplicative congruential algorithm to produce real pseudo-random numbers u_i in the semi-open interval $[0, 1)$:

$$\begin{aligned}k_{1,i} &= (c_1 \times k_{1,i-1}) \bmod m_1 \\k_{2,i} &= (c_2 \times k_{2,i-1}) \bmod m_2 \\k_{3,i} &= (c_3 \times k_{3,i-1}) \bmod m_3 \\k_{4,i} &= (c_4 \times k_{4,i-1}) \bmod m_4 \\u_i &= \left(\frac{k_{1,i}}{m_1} + \frac{k_{2,i}}{m_2} + \frac{k_{3,i}}{m_3} + \frac{k_{4,i}}{m_4} \right) \bmod 1.0\end{aligned}$$

where c_j and m_j , $j = 1, \dots, 4$ are constant integers for each generator and $k_{j,i}$ on the left and right hand of the equations are newly generated integer seeds and old seeds, respectively. The real values u_i give pseudo-random numbers in the semi-open interval $[0, 1)$. If (in the unlikely event) u_i is zero then that value is discarded and a new u_i is generated. The constants c_j are in the range 112 to 127 and the constants m_j are prime numbers in the range 16718909 to 16776971 which are close to $2^{24} = 16777216$. These constants have been chosen so that they give good results with the spectral test, see Knuth [1] and Maclaren [2].

The period of each generator would be at least 2^{92} if it were not for common factors between $(m_1 - 1)$, $(m_2 - 1)$, $(m_3 - 1)$ and $(m_4 - 1)$. However, each should still have a period of at least 2^{80} . Further details of the generators can be obtained from NAG and further discussion of the properties of these generators is given in Maclaren [2] where it was shown that the generated pseudo-random sequences are essentially independent of one another according to the spectral test.

7 References

- [1] Knuth D E (1981) *The Art of Computer Programming (Volume 2)* Addison–Wesley (2nd Edition)
- [2] Maclaren N M (1989) The generation of multiple independent sequences of pseudorandom numbers *Appl. Statist.* **38** 351–359
- [3] Wichmann B A and Hill I D (1982) AS183 An efficient and portable pseudo-random number generator *Appl. Statist.* **31** 188–190

8 Example

This example generates a series of random numbers on each processor on a 2 by 2 logical grid of processors. The routine G05BBFP is used to initialise the seeds and the generators.

8.1 Example Text

```
*      G05BAFP Example Program Text
*      NAG Parallel Library Release 3. NAG Copyright 1999.
*      .. Parameters ..
INTEGER          NOUT, NX
PARAMETER       (NOUT=6,NX=10)
INTEGER          MAG
PARAMETER       (MAG=16909320)
*      .. Local Scalars ..
INTEGER          I, ICNTXT, ICOFF, IFAIL, IGEN, MP, MYCOL, MYROW,
+               N, NP, NPCOL, NPROW
LOGICAL          ROOT
CHARACTER       CNUMOP, TITOP
```

```

CHARACTER*20    FORMT
*
.. Local Arrays ..
DOUBLE PRECISION WORK(NX), X(NX)
INTEGER         IS(5), ISEED(4), IWORK(5)
*
.. External Functions ..
LOGICAL         Z01ACFP
EXTERNAL        Z01ACFP
*
.. External Subroutines ..
EXTERNAL        G05BAFP, G05BBFP, X04BFFP, X04BMFP, Z01AAFP,
+              Z01ABFP, Z01ZAFP
*
.. Intrinsic Functions ..
INTRINSIC       MOD
*
.. Executable Statements ..
ROOT = Z01ACFP()
IF (ROOT) THEN
    WRITE (NOUT,*) 'G05BAFP Example Program Results'
    WRITE (NOUT,*)
END IF
*
MP = 2
NP = 2
*
*   Declare the processor grid
*
IFAIL = 0
CALL Z01AAFP(ICNTXT,MP,NP,IFAIL)
*
*   Initialise the seeds and the generator
CALL Z01ZAFP(ICNTXT,NPROW,NPCOL,MYROW,MYCOL)
*
*   Initialize the seeds and choose a generator number that depends
*   on the processor position on the grid.
*
ISEED(1) = 207*(50*MYROW+19*MYCOL) + 5678212
ISEED(2) = 451*(70*MYROW+31*MYCOL) + 6252478
ISEED(3) = 912*(39*MYROW+56*MYCOL) + 2626279
ISEED(4) = 812*(69*MYROW+78*MYCOL) + 8932937
IGEN = NP*MYROW*4 + MP*MYCOL*6
*
*   Make sure that the seeds are within the maximum value MAG
*
DO 40 I = 1, 4
20  IF (ISEED(I).GT.MAG) THEN
        ISEED(I) = ISEED(I)/2
        GO TO 20
    END IF
40  CONTINUE
*
*   Make sure that the generator is valid
*
IGEN = MOD(IGEN,273)
*
*   Print the seeds and the generator
*
IS(1) = ISEED(1)
IS(2) = ISEED(2)
IS(3) = ISEED(3)
IS(4) = ISEED(4)

```

```

IS(5) = IGEN
IF (ROOT) THEN
  WRITE (NOUT,*)
  WRITE (NOUT,*) 'Seeds and the generator'
  WRITE (NOUT,*)
END IF
FORMT = 'I10'
TITOP = 'Y'
CNUMOP = 'X'
ICOFF = 0
IFAIL = 0
CALL X04BMFP(ICNTXT,NOUT,1,5,IS,1,FORMT,TITOP,CNUMOP,ICOFF,IWORK,
+           1,IFAIL)
CALL G05BBFP(ISEED,IGEN)
*
*
N = 5
*
* Now fill the vectors with random numbers
*
CALL G05BAFP(N,X)
*
* Print the vectors on the root processor
*
IF (ROOT) THEN
  WRITE (NOUT,*)
  WRITE (NOUT,*) 'Random numbers on each processor'
  WRITE (NOUT,*)
END IF
FORMT = 'F12.5'
TITOP = 'Y'
CNUMOP = 'X'
ICOFF = 0
IFAIL = 0
CALL X04BFFP(ICNTXT,NOUT,1,N,X,1,FORMT,TITOP,CNUMOP,ICOFF,WORK,N,
+           IFAIL)

IFAIL = 0
CALL Z01ABFP(ICNTXT,'N',IFAIL)
*
STOP
*
END

```

8.2 Example Data

None.

8.3 Example Results

G05BAFP Example Program Results

Seeds and the generator

Array from logical processor	0,	0			
5678212	6252478	2626279	8932937		0
Array from logical processor	0,	1			
5682145	6266459	2677351	8996273		12
Array from logical processor	1,	0			
5688562	6284048	2661847	8988965		8
Array from logical processor	1,	1			
5692495	6298029	2712919	9052301		20

Random numbers on each processor

Array from logical processor	0,	0			
0.94542	0.10614	0.71538	0.52696		0.66002
Array from logical processor	0,	1			
0.97828	0.94026	0.67519	0.04531		0.03337
Array from logical processor	1,	0			
0.49275	0.67204	0.83978	0.19976		0.49409
Array from logical processor	1,	1			
0.51431	0.41363	0.95747	0.54022		0.20336
