

# NAG Library Routine Document

## C06FKF

**Note:** before using this routine, please read the Users' Note for your implementation to check the interpretation of ***bold italicised*** terms and other implementation-dependent details.

### 1 Purpose

C06FKF calculates the circular convolution or correlation of two real vectors of period  $n$  (using a work array for extra speed).

### 2 Specification

SUBROUTINE C06FKF (JOB, X, Y, N, WORK, IFAIL)

INTEGER JOB, N, IFAIL

REAL (KIND=nag\_wp) X(N), Y(N), WORK(N)

### 3 Description

C06FKF computes:

if JOB = 1, the discrete **convolution** of  $x$  and  $y$ , defined by

$$z_k = \sum_{j=0}^{n-1} x_j y_{k-j} = \sum_{j=0}^{n-1} x_{k-j} y_j;$$

if JOB = 2, the discrete **correlation** of  $x$  and  $y$  defined by

$$w_k = \sum_{j=0}^{n-1} x_j y_{k+j}.$$

Here  $x$  and  $y$  are real vectors, assumed to be periodic, with period  $n$ , i.e.,  $x_j = x_{j\pm n} = x_{j\pm 2n} = \dots$ ;  $z$  and  $w$  are then also periodic with period  $n$ .

**Note:** this usage of the terms 'convolution' and 'correlation' is taken from Brigham (1974). The term 'convolution' is sometimes used to denote both these computations.

If  $\hat{x}$ ,  $\hat{y}$ ,  $\hat{z}$  and  $\hat{w}$  are the discrete Fourier transforms of these sequences, i.e.,

$$\hat{x}_k = \frac{1}{\sqrt{n}} \sum_{j=0}^{n-1} x_j \times \exp\left(-i \frac{2\pi j k}{n}\right), \text{ etc.,}$$

then  $\hat{z}_k = \sqrt{n} \cdot \hat{x}_k \hat{y}_k$  and  $\hat{w}_k = \sqrt{n} \cdot \hat{x}_k \hat{y}_k$  (the bar denoting complex conjugate).

This routine calls the same auxiliary routines as C06FAF and C06FBF to compute discrete Fourier transforms, and there are some restrictions on the value of  $n$ .

### 4 References

Brigham E O (1974) *The Fast Fourier Transform* Prentice-Hall

## 5 Parameters

- 1: JOB – INTEGER *Input*  
*On entry:* the computation to be performed.  
 JOB = 1  

$$z_k = \sum_{j=0}^{n-1} x_j y_{k-j} \text{ (convolution);}$$
 JOB = 2  

$$w_k = \sum_{j=0}^{n-1} x_j y_{k+j} \text{ (correlation).}$$
*Constraint:* JOB = 1 or 2.
- 2: X(N) – REAL (KIND=nag\_wp) array *Input/Output*  
*On entry:* the elements of one period of the vector  $x$ . If X is declared with bounds (0 : N – 1) in the subroutine from which C06FKF is called, then X( $j$ ) must contain  $x_j$ , for  $j = 0, 1, \dots, n - 1$ .  
*On exit:* the corresponding elements of the discrete convolution or correlation.
- 3: Y(N) – REAL (KIND=nag\_wp) array *Input/Output*  
*On entry:* the elements of one period of the vector  $y$ . If Y is declared with bounds (0 : N – 1) in the subroutine from which C06FKF is called, then Y( $j$ ) must contain  $y_j$ , for  $j = 0, 1, \dots, n - 1$ .  
*On exit:* the discrete Fourier transform of the convolution or correlation returned in the array X; the transform is stored in Hermitian form, exactly as described in the document for C06FAF.
- 4: N – INTEGER *Input*  
*On entry:*  $n$ , the number of values in one period of the vectors X and Y. The largest prime factor of N must not exceed 19, and the total number of prime factors of N, counting repetitions, must not exceed 20.  
*Constraint:* N > 1.
- 5: WORK(N) – REAL (KIND=nag\_wp) array *Workspace*
- 6: IFAIL – INTEGER *Input/Output*  
*On entry:* IFAIL must be set to 0, –1 or 1. If you are unfamiliar with this parameter you should refer to Section 3.3 in the Essential Introduction for details.  
 For environments where it might be inappropriate to halt program execution when an error is detected, the value –1 or 1 is recommended. If the output of error messages is undesirable, then the value 1 is recommended. Otherwise, if you are not familiar with this parameter, the recommended value is 0. **When the value –1 or 1 is used it is essential to test the value of IFAIL on exit.**  
*On exit:* IFAIL = 0 unless the routine detects an error or a warning has been flagged (see Section 6).

## 6 Error Indicators and Warnings

If on entry  $IFAIL = 0$  or  $-1$ , explanatory error messages are output on the current error message unit (as defined by  $X04AAF$ ).

Errors or warnings detected by the routine:

$IFAIL = 1$

At least one of the prime factors of  $N$  is greater than 19.

$IFAIL = 2$

$N$  has more than 20 prime factors.

$IFAIL = 3$

On entry,  $N \leq 1$ .

$IFAIL = 4$

On entry,  $JOB \neq 1$  or  $2$ .

## 7 Accuracy

The results should be accurate to within a small multiple of the *machine precision*.

## 8 Further Comments

The time taken is approximately proportional to  $n \times \log n$ , but also depends on the factorization of  $n$ . C06FKF is faster if the only prime factors of  $n$  are 2, 3 or 5; and fastest of all if  $n$  is a power of 2.

## 9 Example

This example reads in the elements of one period of two real vectors  $x$  and  $y$ , and prints their discrete convolution and correlation (as computed by C06FKF). In realistic computations the number of data values would be much larger.

### 9.1 Program Text

```

Program c06fkfe

!      C06FKF Example Program Text

!      Mark 24 Release. NAG Copyright 2012.

!      .. Use Statements ..
      Use nag_library, Only: c06fkf, nag_wp
!      .. Implicit None Statement ..
      Implicit None
!      .. Parameters ..
      Integer, Parameter          :: nin = 5, nout = 6
!      .. Local Scalars ..
      Integer                     :: ieof, ifail, j, n
!      .. Local Arrays ..
      Real (Kind=nag_wp), Allocatable :: work(:), xa(:), xb(:), ya(:), yb(:)
!      .. Executable Statements ..
      Write (nout,*) 'C06FKF Example Program Results'
      Write (nout,*)
!      Skip heading in data file
      Read (nin,*)
loop: Do
      Read (nin,*,Iostat=ieof) n
      If (ieof<0) Exit loop

```

```

Allocate (work(n),xa(n),xb(n),ya(n),yb(n))
Read (nin,*)(xa(j),ya(j),j=1,n)
xb(1:n) = xa(1:n)
yb(1:n) = ya(1:n)

! ifail: behaviour on error exit
!           =0 for hard exit, =1 for quiet-soft, =-1 for noisy-soft
ifail = 0
Call c06fkf(1,xa,ya,n,work,ifail)

Call c06fkf(2,xb,yb,n,work,ifail)

Write (nout,*) '          Convolution Correlation'
Write (nout,*)
Write (nout,99999)(j-1,xa(j),xb(j),j=1,n)
Deallocate (xa,xb,ya,yb,work)
End Do loop

99999 Format (1X,I5,2F13.5)
End Program c06fkfe

```

## 9.2 Program Data

C06FKF Example Program Data

```

9          : n
1.00      0.50
1.00      0.50
1.00      0.50
1.00      0.50
1.00      0.00
0.00      0.00
0.00      0.00
0.00      0.00
0.00      0.00
0.00      0.00      : xa, ya

```

## 9.3 Program Results

C06FKF Example Program Results

	Convolution	Correlation
0	0.50000	2.00000
1	1.00000	1.50000
2	1.50000	1.00000
3	2.00000	0.50000
4	2.00000	0.00000
5	1.50000	0.50000
6	1.00000	1.00000
7	0.50000	1.50000
8	0.00000	2.00000

---