

# NAG Library Routine Document

## F06SKF (ZTBSV)

**Note:** before using this routine, please read the Users' Note for your implementation to check the interpretation of ***bold italicised*** terms and other implementation-dependent details.

### 1 Purpose

F06SKF (ZTBSV) solves a complex triangular banded system of equations with a single right hand side.

### 2 Specification

```
SUBROUTINE F06SKF (UPLO, TRANS, DIAG, N, K, A, LDA, X, INCX)
INTEGER N, K, LDA, INCX
COMPLEX (KIND=nag_wp) A(LDA,*), X(*)
CHARACTER(1) UPLO, TRANS, DIAG
```

The routine may be called by its BLAS name ***ztbsv***.

### 3 Description

F06SKF (ZTBSV) performs one of the matrix-vector operations

$$x \leftarrow A^{-1}x, \quad x \leftarrow A^{-T}x \quad \text{or} \quad x \leftarrow A^{-H}x,$$

where  $A$  is an  $n$  by  $n$  complex triangular band matrix with  $k$  subdiagonals or superdiagonals, and  $x$  is an  $n$ -element complex vector.  $A^{-T}$  denotes  $(A^T)^{-1}$  or equivalently  $(A^{-1})^T$ ;  $A^{-H}$  denotes  $(A^H)^{-1}$  or equivalently  $(A^{-1})^H$ .

No test for singularity or near-singularity of  $A$  is included in this routine. Such tests must be performed before calling this routine.

### 4 References

None.

### 5 Arguments

- |   |              |
|---|--------------|
| 1: UPLO – CHARACTER(1)  | <i>Input</i> |
| <p><i>On entry:</i> specifies whether <math>A</math> is upper or lower triangular.</p> <p>UPLO = 'U'<br/> <math>A</math> is upper triangular.</p> <p>UPLO = 'L'<br/> <math>A</math> is lower triangular.</p> <p><i>Constraint:</i> UPLO = 'U' or 'L'.</p> |              |
| 2: TRANS – CHARACTER(1)   | <i>Input</i> |
| <p><i>On entry:</i> specifies the operation to be performed.</p> <p>TRANS = 'N'<br/> <math>x \leftarrow A^{-1}x.</math></p> <p>TRANS = 'T'<br/> <math>x \leftarrow A^{-T}x.</math></p>  |              |

**TRANS = 'C'**  
 $x \leftarrow A^{-H}x.$

*Constraint:* TRANS = 'N', 'T' or 'C'.

3: **DIAG** – CHARACTER(1)

*Input*

*On entry:* specifies whether  $A$  has nonunit or unit diagonal elements.

**DIAG = 'N'**

The diagonal elements are stored explicitly.

**DIAG = 'U'**

The diagonal elements are assumed to be 1, and are not referenced.

*Constraint:* DIAG = 'N' or 'U'.

4: **N** – INTEGER

*Input*

*On entry:*  $n$ , the order of the matrix  $A$ .

*Constraint:*  $N \geq 0$ .

5: **K** – INTEGER

*Input*

*On entry:*  $k$ , the number of subdiagonals or superdiagonals of the matrix  $A$ .

*Constraint:*  $K \geq 0$ .

6: **A(LDA,\*)** – COMPLEX (KIND=nag\_wp) array

*Input*

**Note:** the second dimension of the array  $A$  must be at least  $N$ .

*On entry:* the  $n$  by  $n$  triangular band matrix  $A$

The matrix is stored in rows 1 to  $k + 1$ , more precisely,

if **UPLO = 'U'**, the elements of the upper triangle of  $A$  within the band must be stored with element  $A_{ij}$  in  $A(k + 1 + i - j, j)$  for  $\max(1, j - k) \leq i \leq j$ ;

if **UPLO = 'L'**, the elements of the lower triangle of  $A$  within the band must be stored with element  $A_{ij}$  in  $A(1 + i - j, j)$  for  $j \leq i \leq \min(n, j + k)$ .

If **DIAG = 'U'**, the diagonal elements of  $A$  are assumed to be 1, and are not referenced.

7: **LDA** – INTEGER

*Input*

*On entry:* the first dimension of the array  $A$  as declared in the (sub)program from which F06SKF (ZTBSV) is called.

*Constraint:*  $LDA \geq K + 1$ .

8: **X(\*)** – COMPLEX (KIND=nag\_wp) array

*Input/Output*

**Note:** the dimension of the array  $X$  must be at least  $\max(1, 1 + (N - 1) \times |\text{INCX}|)$ .

*On entry:* the vector  $x$ .

If  $\text{INCX} > 0$ ,  $x_i$  must be stored in  $X(1 + (i - 1) \times \text{INCX})$ , for  $i = 1, 2, \dots, N$ .

If  $\text{INCX} < 0$ ,  $x_i$  must be stored in  $X(1 - (N - i) \times \text{INCX})$ , for  $i = 1, 2, \dots, N$ .

*On exit:* the updated vector  $x$  stored in the array elements used to supply the original vector  $x$ .

9: **INCX** – INTEGER

*Input*

*On entry:* the increment in the subscripts of  $X$  between successive elements of  $x$ .

*Constraint:*  $\text{INCX} \neq 0$ .

## **6 Error Indicators and Warnings**

None.

## **7 Accuracy**

Not applicable.

## **8 Parallelism and Performance**

F06SKF (ZTBSV) is not threaded in any implementation.

## **9 Further Comments**

None.

## **10 Example**

None.

---