

NAG Library Function Document

nag_complex_bessel_j_seq (s18gkc)

1 Purpose

nag_complex_bessel_j_seq (s18gkc) returns a sequence of values for the Bessel functions $J_{\alpha+n-1}(z)$ or $J_{\alpha-n+1}(z)$ for complex z , non-negative $\alpha < 1$ and $n = 1, 2, \dots, |N| + 1$.

2 Specification

```
#include <nag.h>
#include <nags.h>

void nag_complex_bessel_j_seq (Complex z, double a, Integer nl, Complex b[],
                               NagError *fail)
```

3 Description

nag_complex_bessel_j_seq (s18gkc) evaluates a sequence of values for the Bessel function of the first kind $J_\alpha(z)$, where z is complex and nonzero and α is the order with $0 \leq \alpha < 1$. The $(|N| + 1)$ -member sequence is generated for orders $\alpha, \alpha + 1, \dots, \alpha + |N|$ when $N \geq 0$. Note that $+$ is replaced by $-$ when $N < 0$. For positive orders the function may also be called with $z = 0$, since $J_q(0) = 0$ when $q > 0$. For negative orders the formula

$$J_{-q}(z) = \cos(\pi q)J_q(z) - \sin(\pi q)Y_q(z)$$

is used to generate the required sequence. The appropriate values of $J_q(z)$ and $Y_q(z)$ are obtained by calls to nag_complex_bessel_y (s17dcc) and nag_complex_bessel_j (s17dec).

4 References

Abramowitz M and Stegun I A (1972) *Handbook of Mathematical Functions* (3rd Edition) Dover Publications

5 Arguments

- 1: **z** – Complex *Input*
On entry: the argument z of the function.
Constraint: $\mathbf{z} \neq (0.0, 0.0)$ when $\mathbf{nl} < 0$.
- 2: **a** – double *Input*
On entry: the order α of the first member in the required sequence of function values.
Constraint: $0.0 \leq \mathbf{a} < 1.0$.
- 3: **nl** – Integer *Input*
On entry: the value of N .
Constraint: $\text{abs}(\mathbf{nl}) \leq 101$.
- 4: **b[abs(nl) + 1]** – Complex *Output*
On exit: with **fail.code** = NE_NOERROR or NW_SOME_PRECISION_LOSS, the required sequence of function values: **b**[$n - 1$] contains $J_{\alpha+n-1}(z)$ if $\mathbf{nl} \geq 0$ and $J_{\alpha-n+1}(z)$ otherwise, for $n = 1, 2, \dots, \text{abs}(\mathbf{nl}) + 1$.

5: **fail** – NagError *

Input/Output

The NAG error argument (see Section 3.6 in the Essential Introduction).

6 Error Indicators and Warnings

NE_ALLOC_FAIL

Dynamic memory allocation failed.

See Section 3.2.1.2 in the Essential Introduction for further information.

NE_BAD_PARAM

On entry, argument $\langle value \rangle$ had an illegal value.

NE_INT

On entry, $|nl| = \langle value \rangle$.

Constraint: $|nl| \leq 101$.

On entry, $nl = \langle value \rangle$.

Constraint: when $nl < 0$, $z \neq (0.0, 0.0)$.

NE_INTERNAL_ERROR

An internal error has occurred in this function. Check the function call and any array sizes. If the call is correct then please contact NAG for assistance.

An unexpected error has been triggered by this function. Please contact NAG.

See Section 3.6.6 in the Essential Introduction for further information.

NE_NO_LICENCE

Your licence key may have expired or may not have been installed correctly.

See Section 3.6.5 in the Essential Introduction for further information.

NE_OVERFLOW_LIKELY

Computation abandoned due to the likelihood of overflow.

NE_REAL

On entry, $a = \langle value \rangle$.

Constraint: $a < 1.0$.

On entry, $a = \langle value \rangle$.

Constraint: $a \geq 0.0$.

NE_TERMINATION_FAILURE

Computation abandoned due to failure to satisfy the termination condition.

NE_TOTAL_PRECISION_LOSS

Computation abandoned due to total loss of precision.

NW_SOME_PRECISION_LOSS

Computation completed but some precision has been lost.

7 Accuracy

All constants in `nag_complex_bessel_y` (s17dcc) and `nag_complex_bessel_j` (s17dec) are specified to approximately 18 digits of precision. If t denotes the number of digits of precision in the floating-point arithmetic being used, then clearly the maximum number of correct digits in the results obtained is

limited by $p = \min(t, 18)$. Because of errors in argument reduction when computing elementary functions inside `nag_complex_bessel_y` (s17dcc) and `nag_complex_bessel_j` (s17dec), the actual number of correct digits is limited, in general, by $p - s$, where $s \approx \max(1, |\log_{10} |z||, |\log_{10} |\alpha||)$ represents the number of digits lost due to the argument reduction. Thus the larger the values of $|z|$ and $|\alpha|$, the less the precision in the result.

8 Parallelism and Performance

Not applicable.

9 Further Comments

None.

10 Example

This example evaluates $J_0(z)$, $J_1(z)$, $J_2(z)$ and $J_3(z)$ at $z = 0.6 - 0.8i$, and prints the results.

10.1 Program Text

```

/* nag_complex_bessel_j_seq (s18gkc) Example Program.
 *
 * Copyright 2014 Numerical Algorithms Group.
 *
 * Mark 7, 2002.
 */

#include <nag.h>
#include <stdio.h>
#include <nag_stdlib.h>
#include <nags.h>

int main(void)
{
    Integer    exit_status = 0;
    Complex    z, b[20];
    double     a, alpha;
    Integer    i, nl;
    NagError   fail;

    INIT_FAIL(fail);

    /* Skip heading in data file */
#ifdef _WIN32
    scanf_s("%*[\n]");
#else
    scanf("%*[\n]");
#endif
    printf("nag_complex_bessel_j_seq (s18gkc) Example Program Results\n");
#ifdef _WIN32
    while (scanf_s(" (%lf,%lf) %lf %"NAG_IFMT"%*[\n] ", &z.re, &z.im, &a,
                  &nl) != EOF)
    {
#else
    while (scanf(" (%lf,%lf) %lf %"NAG_IFMT"%*[\n] ", &z.re, &z.im, &a,
                &nl) != EOF)
    {
#endif
        /* nag_complex_bessel_j_seq (s18gkc).
         * Bessel function of the 1st kind J_(alpha+/-n)(z)
         */
        nag_complex_bessel_j_seq(z, a, nl, b, &fail);
        if (fail.code == NE_NOERROR)
        {
            printf("          z          a          nl\n");
            printf(" (%7.3f,%7.3f) %lf          %"NAG_IFMT"\n\n", z.re, z.im, a, nl);
        }
    }
}

```

```

printf("Requested values of J_alpha(Z)\n\n");
alpha = a;
printf("      alpha          J_alpha(z)\n");
for (i = 0; i < ABS(nl) + 1; i++)
  {
    printf("%13.4e  (%13.4e,%13.4e)\n", alpha, b[i].re,
          b[i].im);
    if (nl > 0)
      alpha += 1.0;
    else
      alpha -= 1.0;
  }
}
else
  {
    printf("Error from nag_complex_bessel_j_seq (s18gkc).\n%s\n",
          fail.message);
    exit_status = 1;
    goto END;
  }
}

END:

return exit_status;
}

```

10.2 Program Data

nag_complex_bessel_j_seq (s18gkc) Example Program Data
 (0.6,-0.8) 0.0 3 - Values of z, a and nl

10.3 Program Results

nag_complex_bessel_j_seq (s18gkc) Example Program Results

z	a	nl
(0.600, -0.800)	0.000000	3

Requested values of J_alpha(Z)

alpha	J_alpha(z)
0.0000e+00	(1.0565e+00, 2.4811e-01)
1.0000e+00	(3.5825e-01, -3.7539e-01)
2.0000e+00	(-2.5974e-02, -1.2538e-01)
3.0000e+00	(-1.9369e-02, -8.6380e-03)
