# **NAG Library Routine Document**

### C09ECF

Note: before using this routine, please read the Users' Note for your implementation to check the interpretation of **bold italicised** terms and other implementation-dependent details.

### 1 Purpose

C09ECF computes the two-dimensional multi-level discrete wavelet transform (DWT). The initialization routine C09ABF must be called first to set up the DWT options.

# 2 Specification

```
SUBROUTINE CO9ECF (M, N, A, LDA, LENC, C, NWL, DWTLVM, DWTLVN, ICOMM, IFAIL)

INTEGER M, N, LDA, LENC, NWL, DWTLVM(NWL), DWTLVN(NWL), ICOMM(180), IFAIL

REAL (KIND=nag_wp) A(LDA,N), C(LENC)
```

### 3 Description

C09ECF computes the multi-level DWT of two-dimensional data. For a given wavelet and end extension method, C09ECF will compute a multi-level transform of a matrix A, using a specified number,  $n_l$ , of levels. The number of levels specified,  $n_l$ , must be no more than the value  $l_{\rm max}$  returned in NWL by the initialization routine C09ABF for the given problem. The transform is returned as a set of coefficients for the different levels (packed into a single array) and a representation of the multi-level structure.

The notation used here assigns level 0 to the input matrix, A. Level 1 consists of the first set of coefficients computed: the vertical  $(v_1)$ , horizontal  $(h_1)$  and diagonal  $(d_1)$  coefficients are stored at this level while the approximation  $(a_1)$  coefficients are used as the input to a repeat of the wavelet transform at the next level. This process is continued until, at level  $n_l$ , all four types of coefficients are stored. The output array, C, stores these sets of coefficients in reverse order, starting with  $a_{n_l}$  followed by  $v_{n_l}, h_{n_l}, d_{n_l}, v_{n_{l-1}}, h_{n_{l-1}}, d_{n_{l-1}}, \dots, v_1, h_1, d_1$ .

### 4 References

None.

#### 5 Parameters

1: M – INTEGER Input

On entry: number of rows, m, of data matrix A.

Constraint: this must be the same as the value M passed to the initialization routine C09ABF.

2: N – INTEGER Input

On entry: number of columns, n, of data matrix A.

Constraint: this must be the same as the value N passed to the initialization routine C09ABF.

3: A(LDA,N) - REAL (KIND=nag\_wp) array

On entry: the m by n data matrix A.

Mark 24 C09ECF.1

C09ECF NAG Library Manual

4: LDA – INTEGER Input

On entry: the first dimension of the array A as declared in the (sub)program from which C09ECF is called

Constraint: LDA  $\geq$  M.

5: LENC – INTEGER Input

On entry: the dimension of the array C as declared in the (sub)program from which C09ECF is called. C must be large enough to contain,  $n_{\rm ct}$ , wavelet coefficients. The maximum value of  $n_{\rm ct}$  is returned in NWCT by the call to the initialization routine C09ABF and corresponds to the DWT being continued for the maximum number of levels possible for the given data set. When the number of levels,  $n_l$ , is chosen to be less than the maximum,  $l_{\rm max}$ , then  $n_{\rm ct}$  is correspondingly smaller and LENC can be reduced by noting that the vertical, horizontal and diagonal coefficients are stored at every level and that in addition the approximation coefficients are stored for the final level only. The number of coefficients stored at each level is given by  $3 \times \lceil \bar{m}/2 \rceil \times \lceil \bar{n}/2 \rceil$  for MODE = 'P' in C09ABF and  $3 \times \lfloor (\bar{m} + n_f - 1)/2 \rfloor \times \lfloor (\bar{n} + n_f - 1)/2 \rfloor$  for MODE = 'H', 'W' or 'Z', where the input data is of dimension  $\bar{m} \times \bar{n}$  at that level and  $n_f$  is the filter length NF provided by the call to C09ABF. At the final level the storage is 4/3 times this value to contain the set of approximation coefficients.

Constraint: LENC  $\geq n_{\rm ct}$ , where  $n_{\rm ct}$  is the total number of coefficients that correspond to a transform with NWL levels.

6: C(LENC) – REAL (KIND=nag\_wp) array Output

On exit: the coefficients of a multi-level wavelet transform of the dataset.

Let q(i) denote the number of coefficients (of each type) at level i, for  $i=1,2,\ldots,n_l$ , such that  $q(i)=\mathrm{DWTLVM}(n_l-i+1)\times\mathrm{DWTLVN}(n_l-i+1)$ . Then, letting  $k_1=q(n_l)$  and  $k_{j+1}=k_j+q(n_l-\lceil j/3\rceil+1)$ , for  $j=1,2,\ldots,3n_l$ , the coefficients are stored in C as follows:

C(i), for  $i = 1, 2, ..., k_1$ 

Contains the level  $n_l$  approximation coefficients,  $a_{n_l}$ .

C(i), for  $i = k_j + 1, \dots, k_{j+1}$ 

Contains the level  $n_l - \lceil j/3 \rceil + 1$  vertical, horizontal and diagonal coefficients. These are:

vertical coefficients if  $j \mod 3 = 1$ ;

horizontal coefficients if  $j \mod 3 = 2$ ;

diagonal coefficients if  $j \mod 3 = 0$ ,

for  $j = 1, ..., 3n_l$ .

7: NWL – INTEGER Input

On entry: the number of levels,  $n_l$ , in the multi-level resolution to be performed.

Constraint:  $1 \le \text{NWL} \le l_{\text{max}}$ , where  $l_{\text{max}}$  is the value returned in NWL (the maximum number of levels) by the call to the initialization routine C09ABF.

8: DWTLVM(NWL) – INTEGER array Output

On exit: the number of coefficients in the first dimension for each coefficient type at each level.  $\mathsf{DWTLVM}(i)$  contains the number of coefficients in the first dimension (for each coefficient type computed) at the  $(n_l-i+1)$ th level of resolution, for  $i=1,2,\ldots,n_l$ . Thus for the first  $n_l-1$  levels of resolution,  $\mathsf{DWTLVM}(n_l-i+1)$  is the size of the first dimension of the matrices of vertical, horizontal and diagonal coefficients computed at this level; for the final level of resolution,  $\mathsf{DWTLVM}(1)$  is the size of the first dimension of the matrices of approximation, vertical, horizontal and diagonal coefficients computed.

C09ECF.2 Mark 24

### 9: DWTLVN(NWL) – INTEGER array

Output

On exit: the number of coefficients in the second dimension for each coefficient type at each level. DWTLVN(i) contains the number of coefficients in the second dimension (for each coefficient type computed) at the  $(n_l - i + 1)$ th level of resolution, for  $i = 1, 2, ..., n_l$ . Thus for the first  $n_l - 1$  levels of resolution, DWTLVN( $n_l - i + 1$ ) is the size of the second dimension of the matrices of vertical, horizontal and diagonal coefficients computed at this level; for the final level of resolution, DWTLVN(1) is the size of the second dimension of the matrices of approximation, vertical, horizontal and diagonal coefficients computed.

#### 10: ICOMM(180) – INTEGER array

Communication Array

On entry: contains details of the discrete wavelet transform and the problem dimension as setup in the call to the initialization routine C09ABF.

On exit: contains additional information on the computed transform.

### 11: IFAIL - INTEGER

Input/Output

On entry: IFAIL must be set to 0, -1 or 1. If you are unfamiliar with this parameter you should refer to Section 3.3 in the Essential Introduction for details.

For environments where it might be inappropriate to halt program execution when an error is detected, the value -1 or 1 is recommended. If the output of error messages is undesirable, then the value 1 is recommended. Otherwise, if you are not familiar with this parameter, the recommended value is 0. When the value -1 or 1 is used it is essential to test the value of IFAIL on exit.

On exit: IFAIL = 0 unless the routine detects an error or a warning has been flagged (see Section 6).

# 6 Error Indicators and Warnings

If on entry IFAIL = 0 or -1, explanatory error messages are output on the current error message unit (as defined by X04AAF).

Errors or warnings detected by the routine:

IFAIL = 1

On entry, M is inconsistent with the value passed to the initialization routine C09ABF, or N is inconsistent with the value passed to the initialization routine C09ABF.

IFAIL = 2

On entry, LDA < M.

IFAIL = 3

On entry, LENC  $< n_{\rm ct}^*$ , where  $n_{\rm ct}^*$  is the required number of wavelet coefficients for NWL, the number of levels requested (for the maximum possible number of levels this value is returned in NWCT by the call to the initialization routine C09ABF).

IFAIL = 5

On entry, NWL < 1,

or  $NWL > l_{max}$ , where  $l_{max}$  is the value returned in NWL by the call to the initialization routine C09ABF.

IFAIL = 7

On entry, the initialization routine C09ABF has not been called first or it has been called with WTRANS = 'S', or the communication array ICOMM has become corrupted.

Mark 24 C09ECF.3

### 7 Accuracy

The accuracy of the wavelet transform depends only on the floating point operations used in the convolution and downsampling and should thus be close to *machine precision*.

### **8** Further Comments

The wavelet coefficients at each level can be extracted from the output array C using the information contained in DWTLVM and DWTLVN on exit (see the descriptions of C, DWTLVM and DWTLVN in Section 5). For example, given an input data set, A, denoising can be carried out by applying a thresholding operation to the detail (vertical, horizontal and diagonal) coefficients at every level. The elements  $C(k_1+1)$  to  $C(k_{n_l+1})$ , as described in Section 5, contain the detail coefficients,  $\hat{c}_{ij}$ , for  $i=n_l,n_l-1,\ldots,1$  and  $j=1,2,\ldots,3q(i)$ , where q(i) is the number of each type of coefficient at level i and  $\hat{c}_{ij}=c_{ij}+\sigma\epsilon_{ij}$  and  $\sigma\epsilon_{ij}$  is the transformed noise term. If some threshold parameter  $\alpha$  is chosen, a simple hard thresholding rule can be applied as

$$\bar{c}_{ij} = \begin{cases} 0, & \text{if } |\hat{c}_{ij}| \le \alpha \\ \hat{c}_{ij}, & \text{if } |\hat{c}_{ij}| > \alpha, \end{cases}$$

taking  $\bar{c}_{ij}$  to be an approximation to the required detail coefficient without noise,  $c_{ij}$ . The resulting coefficients can then be used as input to C09EDF in order to reconstruct the denoised signal.

See the references given in the introduction to this chapter for a more complete account of wavelet denoising and other applications.

# 9 Example

This example performs a multi-level resolution transform of a dataset using the Daubechies wavelet (see WAVNAM = 'DB2' in C09ABF) using half-point symmetric end extensions, the maximum possible number of levels of resolution, where the number of coefficients in each level and the coefficients themselves are not changed. The original dataset is then reconstructed using C09EDF.

#### 9.1 Program Text

```
Program c09ecfe
      Mark 24 Release. NAG Copyright 2012.
!
       .. Use Statements ..
      Use nag_library, Only: c09abf, c09ecf, c09edf, nag_wp
      .. Implicit None Statement ..
!
      Implicit None
       .. Parameters .
!
                                            :: nin = 5, nout = 6
      Integer, Parameter
!
      .. Local Scalars ..
                                            :: i, i1, i2, ifail, ilevel, iskip,
  itype_coeffs, j1, jstart, lda, ldb,
  lenc, m, n, nf, nwcn, nwct, nwl
      Integer
      Character (10)
                                            :: mode, wavnam, wtrans
      .. Local Arrays ..
!
      Real (Kind=nag_wp), Allocatable
                                           :: a(:,:), b(:,:), c(:)
                                            :: dwtlvm(:), dwtlvn(:)
      Integer, Allocatable
                                            :: icomm(180)
!
      .. Executable Statements ..
      Write (nout,*) 'CO9ECF Example Program Results'
      Write (nout,*)
      Skip heading in data file
1
      Read (nin,*)
      Read problem parameters
      Read (nin,*) m, n
      Read (nin,*) wavnam, mode
      lda = m
      ldb = m
      Allocate (a(lda,n),b(ldb,n))
```

C09ECF.4 Mark 24

```
Write (nout, 99999) wavnam, mode, m, n
Read data array and write it out
Do i = 1, m
 Read (nin,*) a(i,1:n)
End Do
Write (nout,*) ' Input Data
                             A :'
Do i = 1, m
 Write (nout, 99998) a(i,1:n)
End Do
Query wavelet filter dimensions
For Multi-Resolution Analysis, decomposition, wtrans = 'M'
wtrans = 'Multilevel'
ifail = 0
Call c09abf(wavnam,wtrans,mode,m,n,nwl,nf,nwct,nwcn,icomm,ifail)
lenc = nwct
Allocate (c(lenc),dwtlvm(nwl),dwtlvn(nwl))
Perform Discrete Wavelet transform
ifail = 0
Call c09ecf(m,n,a,lda,lenc,c,nwl,dwtlvm,dwtlvn,icomm,ifail)
Write (nout,99997) nwl
Write (nout, 99996)
Write (nout, 99995) dwtlvm(1:nwl)
Write (nout, 99994)
Write (nout, 99995) dwtlvn(1:nwl)
Extract coefficients
Write (nout, 99993)
jstart = 1
Do ilevel = nwl, 1, -1
  Write (nout,99992) ilevel, dwtlvm(nwl-ilevel+1), dwtlvn(nwl-ilevel+1)
  iskip = dwtlvm(nwl-ilevel+1)
  i2 = iskip*dwtlvn(nwl-ilevel+1) - 1
  Do itype_coeffs = 1, 4
    Select Case (itype_coeffs)
    Case (1)
      If (ilevel==nwl) Then
        Write (nout, 99991) 'Approximation coefficients'
      End If
    Case (2)
      Write (nout, 99991) 'Vertical coefficients
    Case (3)
      Write (nout,99991) 'Horizontal coefficients
    Case (4)
      Write (nout, 99991) 'Diagonal coefficients
    End Select
    If (itype_coeffs>1 .Or. ilevel==nwl) Then
      Do i1 = jstart, jstart + iskip - 1
        Write (nout, 99989)(c(j1), j1=i1, i1+i2, iskip)
      End Do
      jstart = jstart + i2 + 1
    End If
  End Do
End Do
Reconstruct original data
ifail = 0
Call c09edf(nwl,lenc,c,m,n,b,ldb,icomm,ifail)
Write (nout, 99990)
Do i = 1, m
  Write (nout, 99998) b(i,1:n)
End Do
```

Mark 24 C09ECF.5

C09ECF NAG Library Manual

```
: ',I4/1X,'
                                                                    : ',I4/)
99998 Format (8(F8.4,1X):)
99997 Format (/1X,' Number of Levels : ',I10)
99996 Format (1X,' Number of coefficients in 1st dimension for each level :')
99995 Format (8(I8,1X):)
99994 Format (1X,' Number of coefficients in 2nd dimension for each level :') 99993 Format (/1X,' Wavelet coefficients C : ')
99992 Format (1X,55('-')/1X,' Level : ',I10,'; output is ',I10,' by ',I10/1X, &
        55('-'))
99991 Format (1X,A28,': ')
                                                    B : ')
99990 Format (/1X,' Reconstruction
99989 Format (4X,5(F8.4,1X):)
    End Program c09ecfe
9.2 Program Data
CO9ECF Example Program Data
                                         : m, n
 DB2 Half : wavnam, mode
  3.0000 7.0000 9.0000 1.0000 9.0000 1.0000 0.0000
9.0000 9.0000 3.0000 3.0000 4.0000 1.0000 2.0000 4.0000

      7.0000
      8.0000
      1.0000
      3.0000
      8.0000
      9.0000
      3.0000
      3.0000

      1.0000
      1.0000
      1.0000
      2.0000
      8.0000
      4.0000
      0.0000

      1.0000
      2.0000
      4.0000
      5.0000
      5.0000
      4.0000

  2.0000 2.0000 5.0000 7.0000 3.0000 6.0000 6.0000 8.0000
  7.0000 9.0000 3.0000 1.0000 3.0000 4.0000 7.0000 2.0000
9.3 Program Results
 CO9ECF Example Program Results
  MLDWT :: Wavelet : DB2
             End mode : Half
             M : 7
  Input Data
                   A :

      3.0000
      7.0000
      9.0000
      1.0000
      9.0000
      9.0000
      1.0000

      9.0000
      9.0000
      3.0000
      3.0000
      4.0000
      1.0000
      2.0000

      7.0000
      8.0000
      1.0000
      3.0000
      8.0000
      9.0000
      3.0000

                                                                             0.0000
                                                                             4.0000
3.0000
  1.0000 1.0000 1.0000 1.0000 2.0000 8.0000 4.0000 0.0000
  1.0000 2.0000 4.0000 6.0000 5.0000 6.0000 5.0000 4.0000
  2.0000 2.0000 5.0000 7.0000
7.0000 9.0000 3.0000 1.0000
                                             3.0000 6.0000 6.0000
3.0000 4.0000 7.0000
                                                                             8.0000
2.0000
  Number of Levels :
  Number of coefficients in 1st dimension for each level:
  Number of coefficients in 2nd dimension for each level:
  Wavelet coefficients C:
 _____
                     2; output is 4 by
 _____
  Approximation coefficients :
      24.9724 25.6017 20.8900 7.9280
27.6100 27.0955 18.7941 8.2804
      11.2663 11.0273 19.6410 18.6651
      27.6050 26.6443 14.5913 18.0835
  Vertical coefficients :
      -2.5552 -6.1078 -4.0629 8.2136
      -1.6061 -7.2355 -3.3633 7.6075
      -0.2225 -1.6283 -0.5301 3.7415
-0.9052 -6.5810 0.8023 1.8591
  Horizontal coefficients :
      -3.8069 -3.0730 2.1121 -1.8525
      -2.7548 -4.5949 -0.8321 -4.8155
```

C09ECF.6 Mark 24

```
4.8398 4.5104 -1.5308 -0.6456
   -6.4332 -4.5381 2.4753 6.8224
Diagonal coefficients
   -0.8978 -0.2326 -1.2515
                                 2.6346
    0.5708 -4.9783 -1.5309
                                 6.4569
   -0.1854 -1.8430 0.2426 -0.0754
    0.0345 7.1864 1.5938 -5.9745
Level: 1; output is 5 by
Vertical coefficients :

      -2.5981
      4.6471
      2.5392
      -2.8415
      -0.2165

      -1.3203
      -0.0592
      3.0490
      -2.5837
      1.0458

   -0.4330 -1.6405 -1.1752 0.2533 -2.3448
   -0.4118 -0.0682 -2.4608 -0.0167 0.4387
-1.5368 -1.1450 -0.5547 4.5936 -3.6863
Horizontal coefficients
   -4.3301 -1.8170 0.8023 5.7566 -2.8146
    4.3089 3.6908 0.8349 3.4653 1.7108
   -1.5311 -1.0736 1.5257 0.0212 -0.9608
   2.8873 3.1148 -1.9118 -0.4007 -2.2377 -2.7611 2.4453 -0.3705
                                 -0.4007 -1.5302
                                           4.3448
Diagonal coefficients
   -1.5000 4.4151 -0.0057 -0.8236 -1.1250
   -0.1953 -2.9530 1.8840 -1.7635 0.9877
-0.4330 0.2745 1.1450 0.4632 -0.5547
-0.3538 -0.3215 0.6462 1.3705 -1.2778
    Reconstruction
3.0000 7.0000 9.0000 1.0000 9.0000
                                                 9.0000 1.0000
                                                                     0.0000
        9.0000 3.0000 3.0000
                                      4.0000 1.0000 2.0000
                                                                     4.0000
9.0000
7.0000 8.0000 1.0000 3.0000
                                      8.0000
                                                9.0000 3.0000
                                                                     3.0000
                                      2.0000

    1.0000
    1.0000
    1.0000

    2.0000
    4.0000
    6.0000

    2.0000
    5.0000
    7.0000

                                                                     0.0000
1.0000
                                                8.0000 4.0000
1.0000
                                        5.0000
                                                  6.0000
                                                            5.0000
                                                                      4.0000
                                                  6.0000 6.0000
                                                                     8.0000
                                        3.0000
2.0000
7.0000 9.0000 3.0000 1.0000
                                      3.0000 4.0000 7.0000
                                                                     2.0000
```

Mark 24 C09ECF.7 (last)