

NAG Library Routine Document

F06THF

Note: before using this routine, please read the Users' Note for your implementation to check the interpretation of *bold italicised* terms and other implementation-dependent details.

1 Purpose

F06THF forms the complex m by n rectangular or trapezoidal matrix A given by

$$a_{ij} = \begin{cases} \text{diag} & \text{if } i = j \\ \text{const} & \text{if } i \neq j \end{cases}$$

2 Specification

```
SUBROUTINE F06THF (MATRIX, M, N, CON, DIAG, A, LDA)
  INTEGER          M, N, LDA
  COMPLEX (KIND=nag_wp) CON, DIAG, A(LDA,*)
  CHARACTER(1)    MATRIX
```

3 Description

None.

4 References

None.

5 Arguments

- | | | |
|----|---|--------------|
| 1: | MATRIX – CHARACTER(1) <i>On entry:</i> the matrix type. MATRIX = 'G' General matrix. MATRIX = 'U' Upper trapezoidal matrix (upper triangular if $m = n$). MATRIX = 'L' Lower trapezoidal matrix (lower triangular if $m = n$). <i>Constraint:</i> MATRIX = 'G', 'U' or 'L'. | <i>Input</i> |
| 2: | M – INTEGER <i>On entry:</i> m , the number of rows of the matrix A . <i>Constraint:</i> $M \geq 0$. | <i>Input</i> |
| 3: | N – INTEGER <i>On entry:</i> n , the number of columns of the matrix A . <i>Constraint:</i> $N \geq 0$. | <i>Input</i> |
| 4: | CON – COMPLEX (KIND=nag_wp) <i>On entry:</i> the value to be assigned to the off-diagonal elements of A . | <i>Input</i> |

- 5: DIAG – COMPLEX (KIND=nag_wp) *Input*
On entry: the value to be assigned to the diagonal elements of *A*.
- 6: A(LDA,*) – COMPLEX (KIND=nag_wp) array *Output*
Note: the second dimension of the array *A* must be at least *N*.
On exit: the *m* by *n* general or trapezoidal matrix *A*.
 If MATRIX = 'U', *A* is upper trapezoidal and the elements of the array below the diagonal are not referenced.
 If MATRIX = 'L', *A* is lower trapezoidal and the elements of the array above the diagonal are not referenced.
- 7: LDA – INTEGER *Input*
On entry: the first dimension of the array *A* as declared in the (sub)program from which F06THF is called.
Constraint: $LDA \geq \max(1, M)$.

6 Error Indicators and Warnings

None.

7 Accuracy

Not applicable.

8 Parallelism and Performance

F06THF is not threaded in any implementation.

9 Further Comments

None.

10 Example

None.
