

NAG Library Function Document

nag_matop_real_gen_matrix_cond_num (f01jbc)

1 Purpose

nag_matop_real_gen_matrix_cond_num (f01jbc) computes an estimate of the absolute condition number of a matrix function f at a real n by n matrix A in the 1-norm. Numerical differentiation is used to evaluate the derivatives of f when they are required.

2 Specification

```
#include <nag.h>
#include <nagf01.h>
void nag_matop_real_gen_matrix_cond_num (Integer n, double a[], Integer pda,
                                         void (*f)(Integer *iflag, Integer nz, const Complex z[], Complex fz[], Nag_Comm *comm),
                                         Nag_Comm *comm, Integer *iflag, double *condabs, double *norma,
                                         double *normfa, NagError *fail)
```

3 Description

The absolute condition number of f at A , $\text{cond}_{\text{abs}}(f, A)$ is given by the norm of the Fréchet derivative of f , $L(A)$, which is defined by

$$\|L(X)\| := \max_{E \neq 0} \frac{\|L(X, E)\|}{\|E\|},$$

where $L(X, E)$ is the Fréchet derivative in the direction E . $L(X, E)$ is linear in E and can therefore be written as

$$\text{vec}(L(X, E)) = K(X)\text{vec}(E),$$

where the vec operator stacks the columns of a matrix into one vector, so that $K(X)$ is $n^2 \times n^2$. nag_matop_real_gen_matrix_cond_num (f01jbc) computes an estimate γ such that $\gamma \leq \|K(X)\|_1$, where $\|K(X)\|_1 \in [n^{-1}\|L(X)\|_1, n\|L(X)\|_1]$. The relative condition number can then be computed via

$$\text{cond}_{\text{rel}}(f, A) = \frac{\text{cond}_{\text{abs}}(f, A)\|A\|_1}{\|f(A)\|_1}.$$

The algorithm used to find γ is detailed in Section 3.4 of Higham (2008).

The function f is supplied via function **f** which evaluates $f(z_i)$ at a number of points z_i .

4 References

Higham N J (2008) *Functions of Matrices: Theory and Computation* SIAM, Philadelphia, PA, USA

5 Arguments

1: **n** – Integer *Input*

On entry: n , the order of the matrix A .

Constraint: $\mathbf{n} \geq 0$.

6:	iflag – Integer *	Output
<i>On exit:</i> iflag = 0, unless iflag has been set nonzero inside f , in which case iflag will be the value set and fail will be set to fail.code = NE_USER_STOP.		
7:	condA – double *	Output
<i>On exit:</i> an estimate of the absolute condition number of f at A .		
8:	normA – double *	Output
<i>On exit:</i> the 1-norm of A .		
9:	normfa – double *	Output
<i>On exit:</i> the 1-norm of $f(A)$.		
10:	fail – NagError *	Input/Output
<i>The NAG error argument (see Section 3.6 in the Essential Introduction).</i>		

6 Error Indicators and Warnings

NE_ALLOC_FAIL

Allocation of memory failed.

NE_BAD_PARAM

On entry, argument $\langle\text{value}\rangle$ had an illegal value.

NE_INT

On entry, **n** = $\langle\text{value}\rangle$.
Constraint: **n** ≥ 0 .

NE_INT_2

On entry, **pda** = $\langle\text{value}\rangle$ and **n** = $\langle\text{value}\rangle$.
Constraint: **pda** $\geq \mathbf{n}$.

NE_INTERNAL_ERROR

An internal error has occurred in this function. Check the function call and any array sizes. If the call is correct then please contact NAG for assistance.

An internal error occurred when estimating the norm of the Fréchet derivative of f at A . Please contact NAG.

An internal error occurred when evaluating the matrix function $f(A)$. You can investigate further by calling nag_matop_real_gen_matrix_fun_num (f01elc) with the matrix A and the function f .

NE_USER_STOP

iflag has been set nonzero by the user-supplied function.

7 Accuracy

nag_matop_real_gen_matrix_cond_num (f01jbc) uses the norm estimation function nag_linsys_real_gen_norm_rcomm (f04ydc) to estimate a quantity γ , where $\gamma \leq \|K(X)\|_1$ and $\|K(X)\|_1 \in [n^{-1}\|L(X)\|_1, n\|L(X)\|_1]$. For further details on the accuracy of norm estimation, see the documentation for nag_linsys_real_gen_norm_rcomm (f04ydc).

8 Parallelism and Performance

`nag_matop_real_gen_matrix_cond_num` (f01jbc) is threaded by NAG for parallel execution in multithreaded implementations of the NAG Library.

`nag_matop_real_gen_matrix_cond_num` (f01jbc) makes calls to BLAS and/or LAPACK routines, which may be threaded within the vendor library used by this implementation. Consult the documentation for the vendor library for further information.

In these implementations, this may make calls to the user supplied functions from within an OpenMP parallel region. Thus OpenMP directives within the user functions should be avoided, unless you are using the same OpenMP runtime library (which normally means using the same compiler) as that used to build your NAG Library implementation, as listed in the Installers' Note. You must also ensure that you use the NAG communication argument `comm` in a thread safe manner, which is best achieved by only using it to supply read-only data to the user functions.

Please consult the Users' Note for your implementation for any additional implementation-specific information.

9 Further Comments

The matrix function is computed using the underlying matrix function routine `nag_matop_real_gen_matrix_fun_num` (f01elc). Approximately $6n^2$ of real allocatable memory is required by the routine, in addition to the memory used by the underlying matrix function routine.

If only $f(A)$ is required, without an estimate of the condition number, then it is far more efficient to use the underlying matrix function routine.

The complex analogue of this function is `nag_matop_complex_gen_matrix_cond_num` (f01kbc).

10 Example

This example estimates the absolute and relative condition numbers of the matrix function $\cos 2A$ where

$$A = \begin{pmatrix} -1 & -1 & -2 & 1 \\ 0 & 1 & -1 & 0 \\ -1 & -2 & 1 & -1 \\ 0 & -1 & 0 & -1 \end{pmatrix}.$$

10.1 Program Text

```
/* nag_matop_real_gen_matrix_cond_num (f01jbc) Example Program.
*
* Copyright 2013 Numerical Algorithms Group.
*
* Mark 24, 2013.
*/
#include <math.h>
#include <nag.h>
#include <nag_stdlib.h>
#include <nagf01.h>
#include <nagx02.h>
#include <nagx04.h>

#ifndef __cplusplus
extern "C" {
#endif
    static void NAG_CALL f(Integer *iflag, Integer nz, const Complex z[],
                           Complex fz[], Nag_Comm *comm);
#endif
#define A(I,J) a[J*pda + I]

int main(void)
```

```
{
/* Scalars */
Integer      exit_status = 0;
Integer      i, iflag, j, n, pda;
double       conda, cond_rel, eps, norma, normfa;
/* Arrays */
static double ruser[1] = {-1.0};
double       *a = 0;
/* Nag Types */
Nag_OrderType  order = Nag_ColMajor;
Nag_Comm      comm;
NagError      fail;

INIT_FAIL(fail);

/* Output preamble */
printf("nag_matop_real_gen_matrix_cond_num (f01jbc) ");
printf("Example Program Results\n\n");

/* For communication with user-supplied functions: */
comm.user = ruser;

fflush(stdout);

/* Skip heading in data file */
scanf("%*[^\n] ");

/* Read in the problem size */
scanf("%ld%*[^\n]", &n);

pda = n;
if (!(a = NAG_ALLOC((pda)*(n), double))) {
    printf("Allocation failure\n");
    exit_status = -1;
    goto END;
}

/* Read in the matrix A from data file */
for (i = 0; i < n; i++)
    for (j = 0; j < n; j++) scanf("%lf", &a(i, j));
scanf("%*[^\n] ");

/* Print matrix A using nag_gen_real_mat_print (x04cac)
 * Print real general matrix (easy-to-use)
 */
nag_gen_real_mat_print (order, Nag_GeneralMatrix, Nag_NonUnitDiag,
                        n, n, a, pda, "A", NULL, &fail);
if (fail.code != NE_NOERROR) {
    printf("Error from nag_gen_real_mat_print (x04cac)\n%s\n",
           fail.message);
    exit_status = 2;
    goto END;
}

/* Find absolute condition number estimate of f(A) for a real matrix A using
 * nag_matop_real_gen_matrix_cond_num (f01jbc)
 * which uses numerical differentiation.
 */
nag_matop_real_gen_matrix_cond_num (n, a, pda, f, &comm, &iflag,
                                    &conda, &norma, &normfa, &fail);
if (fail.code != NE_NOERROR) {
    printf("Error from nag_matop_real_gen_matrix_cond_num (f01jbc)\n%s\n",
           fail.message);
    exit_status = 1;
    goto END;
}

/* Print absolute condition number estimate */
printf("\nf(A) = cos(2A)\n");
printf("Estimated absolute condition number is: %7.2f\n", conda);
```

```

/* nag_machine_precision (x02ajc) The machine precision */
eps = nag_machine_precision;

/* Find relative condition number estimate */
if ( normfa>eps) {
    cond_rel = cond_a * norma/normfa;
    printf("Estimated relative condition number is: %7.2f\n",cond_rel);
}
else {
    printf("The estimated norm of f(A) is effectively zero");
    printf("and so the relative condition number is undefined.\n");
}

END:
NAG_FREE(a);
return exit_status;
}

static void NAG_CALL f(Integer *iflag, Integer nz, const Complex z[],
                      Complex fz[], Nag_Comm *comm)
{
    /* Scalars */
    Integer j;
    if (comm->user[0] == -1.0)
    {
        printf("(User-supplied callback f, first invocation.)\n");
        comm->user[0] = 0.0;
    }
    for (j = 0; j < nz; j++) {
        /*Complex representation of cos 2z */
        fz[j].re = cos(2.0*z[j].re)*cosh(2.0*z[j].im);
        fz[j].im = -sin(2.0*z[j].re)*sinh(2.0*z[j].im);
    }
    /* Set iflag nonzero to terminate execution for any reason.*/
    *iflag = 0;
}

```

10.2 Program Data

```
nag_matop_real_gen_matrix_cond_num (f01jbc) Example Program Data

4                               :Value of n

-1.0   -1.0   -2.0   1.0
 0.0    1.0   -1.0   0.0
-1.0   -2.0    1.0   -1.0
 0.0   -1.0    0.0   -1.0  :End of matrix a
```

10.3 Program Results

```
nag_matop_real_gen_matrix_cond_num (f01jbc) Example Program Results

A
      1         2         3         4
1   -1.0000   -1.0000   -2.0000   1.0000
2    0.0000    1.0000   -1.0000   0.0000
3   -1.0000   -2.0000    1.0000   -1.0000
4    0.0000   -1.0000    0.0000   -1.0000
(User-supplied callback f, first invocation.)

f(A) = cos(2A)
Estimated absolute condition number is:    4.10
Estimated relative condition number is:  14.48
```
