

NAG Library Function Document

nag_matop_real_gen_matrix_cond_num (f01jbc)

1 Purpose

nag_matop_real_gen_matrix_cond_num (f01jbc) computes an estimate of the absolute condition number of a matrix function f at a real n by n matrix A in the 1-norm. Numerical differentiation is used to evaluate the derivatives of f when they are required.

2 Specification

```
#include <nag.h>
#include <nagf01.h>
void nag_matop_real_gen_matrix_cond_num (Integer n, double a[], Integer pda,
                                         void (*f)(Integer *iflag, Integer nz, const Complex z[], Complex fz[], Nag_Comm *comm),
                                         Nag_Comm *comm, Integer *iflag, double *cond, double *norma,
                                         double *normfa, NagError *fail)
```

3 Description

The absolute condition number of f at A , $\text{cond}_{\text{abs}}(f, A)$ is given by the norm of the Fréchet derivative of f , $L(A)$, which is defined by

$$\|L(X)\| := \max_{E \neq 0} \frac{\|L(X, E)\|}{\|E\|},$$

where $L(X, E)$ is the Fréchet derivative in the direction E . $L(X, E)$ is linear in E and can therefore be written as

$$\text{vec}(L(X, E)) = K(X)\text{vec}(E),$$

where the vec operator stacks the columns of a matrix into one vector, so that $K(X)$ is $n^2 \times n^2$. nag_matop_real_gen_matrix_cond_num (f01jbc) computes an estimate γ such that $\gamma \leq \|K(X)\|_1$, where $\|K(X)\|_1 \in [n^{-1}\|L(X)\|_1, n\|L(X)\|_1]$. The relative condition number can then be computed via

$$\text{cond}_{\text{rel}}(f, A) = \frac{\text{cond}_{\text{abs}}(f, A)\|A\|_1}{\|f(A)\|_1}.$$

The algorithm used to find γ is detailed in Section 3.4 of Higham (2008).

The function f is supplied via function **f** which evaluates $f(z_i)$ at a number of points z_i .

4 References

Higham N J (2008) *Functions of Matrices: Theory and Computation* SIAM, Philadelphia, PA, USA

5 Arguments

- | | | |
|----|--|--------------|
| 1: | n – Integer | <i>Input</i> |
| | <i>On entry:</i> n , the order of the matrix A . | |
| | <i>Constraint:</i> $\mathbf{n} \geq 0$. | |

2: **a**[*dim*] – double *Input/Output*

Note: the dimension, *dim*, of the array **a** must be at least **pda** × **n**.

The (*i*, *j*)th element of the matrix *A* is stored in **a**[(*j* − 1) × **pda** + *i* − 1].

On entry: the *n* by *n* matrix *A*.

On exit: the *n* by *n* matrix, *f*(*A*).

3: **pda** – Integer *Input*

On entry: the stride separating matrix row elements in the array **a**.

Constraint: **pda** ≥ **n**.

4: **f** – function, supplied by the user *External Function*

The function **f** evaluates *f*(*z_i*) at a number of points *z_i*.

The specification of **f** is:

```
void f (Integer *iflag, Integer nz, const Complex z[], Complex fz[],
        Nag_Comm *comm)
```

1: **iflag** – Integer * *Input/Output*

On entry: **iflag** will be zero.

On exit: **iflag** should either be unchanged from its entry value of zero, or may be set nonzero to indicate that there is a problem in evaluating the function *f*(*z*); for instance *f*(*z*) may not be defined. If **iflag** is returned as nonzero then nag_matop_real_gen_matrix_cond_num (f01jbc) will terminate the computation, with fail.code = NE_USER_STOP.

2: **nz** – Integer *Input*

On entry: *n_z*, the number of function values required.

3: **z[nz]** – const Complex *Input*

On entry: the *n_z* points *z₁, z₂, ..., z_{n_z}* at which the function *f* is to be evaluated.

4: **fz[nz]** – Complex *Output*

On exit: the *n_z* function values. **fz**[*i* − 1] should return the value *f*(*z_i*), for *i* = 1, 2, ..., *n_z*. If *z_i* lies on the real line, then so must *f*(*z_i*).

5: **comm** – Nag_Comm * *Output*

Pointer to structure of type Nag_Comm; the following members are relevant to **f**.

user – double *

iuser – Integer *

p – Pointer

The type Pointer will be `void *`. Before calling nag_matop_real_gen_matrix_cond_num (f01jbc) you may allocate memory and initialize these pointers with various quantities for use by **f** when called from nag_matop_real_gen_matrix_cond_num (f01jbc) (see Section 3.2.1.1 in the Essential Introduction).

5: **comm** – Nag_Comm * *Input*

The NAG communication argument (see Section 3.2.1.1 in the Essential Introduction).

6:	iflag – Integer *	Output
<i>On exit:</i> iflag = 0, unless iflag has been set nonzero inside f , in which case iflag will be the value set and fail will be set to fail.code = NE_USER_STOP.		
7:	condA – double *	Output
<i>On exit:</i> an estimate of the absolute condition number of f at A .		
8:	normA – double *	Output
<i>On exit:</i> the 1-norm of A .		
9:	normfa – double *	Output
<i>On exit:</i> the 1-norm of $f(A)$.		
10:	fail – NagError *	Input/Output
<i>The NAG error argument (see Section 3.6 in the Essential Introduction).</i>		

6 Error Indicators and Warnings

NE_ALLOC_FAIL

Dynamic memory allocation failed.

See Section 3.2.1.2 in the Essential Introduction for further information.

NE_BAD_PARAM

On entry, argument $\langle\text{value}\rangle$ had an illegal value.

NE_INT

On entry, **n** = $\langle\text{value}\rangle$.

Constraint: **n** ≥ 0 .

NE_INT_2

On entry, **pda** = $\langle\text{value}\rangle$ and **n** = $\langle\text{value}\rangle$.

Constraint: **pda** $\geq \text{n}$.

NE_INTERNAL_ERROR

An internal error has occurred in this function. Check the function call and any array sizes. If the call is correct then please contact NAG for assistance.

An internal error occurred when estimating the norm of the Fréchet derivative of f at A . Please contact NAG.

An internal error occurred when evaluating the matrix function $f(A)$. You can investigate further by calling nag_matop_real_gen_matrix_fun_num (f01elc) with the matrix A and the function f .

An unexpected error has been triggered by this function. Please contact NAG.

See Section 3.6.6 in the Essential Introduction for further information.

NE_NO_LICENCE

Your licence key may have expired or may not have been installed correctly.

See Section 3.6.5 in the Essential Introduction for further information.

NE_USER_STOP

iflag has been set nonzero by the user-supplied function.

7 Accuracy

`nag_matop_real_gen_matrix_cond_num` (f01jbc) uses the norm estimation function `nag_linsys_real_gen_norm_rcomm` (f04ydc) to estimate a quantity γ , where $\gamma \leq \|K(X)\|_1$ and $\|K(X)\|_1 \in [n^{-1}\|L(X)\|_1, n\|L(X)\|_1]$. For further details on the accuracy of norm estimation, see the documentation for `nag_linsys_real_gen_norm_rcomm` (f04ydc).

8 Parallelism and Performance

`nag_matop_real_gen_matrix_cond_num` (f01jbc) is threaded by NAG for parallel execution in multithreaded implementations of the NAG Library. In these implementations, this function may make calls to the user-supplied functions from within an OpenMP parallel region. Thus OpenMP pragmas within the user functions can only be used if you are compiling the user-supplied function and linking the executable in accordance with the instructions in the Users' Note for your implementation. You must also ensure that you use the NAG communication argument **comm** in a thread safe manner, which is best achieved by only using it to supply read-only data to the user functions.

`nag_matop_real_gen_matrix_cond_num` (f01jbc) makes calls to BLAS and/or LAPACK routines, which may be threaded within the vendor library used by this implementation. Consult the documentation for the vendor library for further information.

Please consult the X06 Chapter Introduction for information on how to control and interrogate the OpenMP environment used within this function. Please also consult the Users' Note for your implementation for any additional implementation-specific information.

9 Further Comments

The matrix function is computed using the underlying matrix function routine `nag_matop_real_gen_matrix_fun_num` (f01elc). Approximately $6n^2$ of real allocatable memory is required by the routine, in addition to the memory used by the underlying matrix function routine.

If only $f(A)$ is required, without an estimate of the condition number, then it is far more efficient to use the underlying matrix function routine.

The complex analogue of this function is `nag_matop_complex_gen_matrix_cond_num` (f01kbc).

10 Example

This example estimates the absolute and relative condition numbers of the matrix function $\cos 2A$ where

$$A = \begin{pmatrix} -1 & -1 & -2 & 1 \\ 0 & 1 & -1 & 0 \\ -1 & -2 & 1 & -1 \\ 0 & -1 & 0 & -1 \end{pmatrix}.$$

10.1 Program Text

```
/* nag_matop_real_gen_matrix_cond_num (f01jbc) Example Program.
*
* Copyright 2014 Numerical Algorithms Group.
*
* Mark 24, 2013.
*/
#include <math.h>
#include <nag.h>
#include <nag_stlib.h>
#include <nagf01.h>
#include <nagx02.h>
#include <nagx04.h>

#ifndef __cplusplus
extern "C" {
#endif
```

```

    static void NAG_CALL f(Integer *iflag, Integer nz, const Complex z[],
                           Complex fz[], Nag_Comm *comm);
#endif __cplusplus
}
#endif

#define A(I,J) a[J*pda + I]

int main(void)
{
    /* Scalars */
    Integer         exit_status = 0;
    Integer         i, iflag, j, n, pda;
    double          conda, cond_rel, eps, norma, normfa;
    /* Arrays */
    static double   ruser[1] = {-1.0};
    double          *a = 0;
    /* Nag Types */
    Nag_OrderType   order = Nag_ColMajor;
    Nag_Comm        comm;
    NagError        fail;

    INIT_FAIL(fail);

    /* Output preamble */
    printf("nag_matop_real_gen_matrix_cond_num (f01jbc) ");
    printf("Example Program Results\n\n");

    /* For communication with user-supplied functions: */
    comm.user = ruser;

    fflush(stdout);

    /* Skip heading in data file */
#ifndef _WIN32
    scanf_s("%*[^\n] ");
#else
    scanf("%*[^\n] ");
#endif

    /* Read in the problem size */
#ifndef _WIN32
    scanf_s("%"NAG_IFMT"%*[^\n]", &n);
#else
    scanf("%"NAG_IFMT"%*[^\n]", &n);
#endif

    pda = n;
    if (!(a = NAG_ALLOC((pda)*(n), double))) {
        printf("Allocation failure\n");
        exit_status = -1;
        goto END;
    }

    /* Read in the matrix A from data file */
    for (i = 0; i < n; i++)
#ifndef _WIN32
        for (j = 0; j < n; j++) scanf_s("%lf", &A(i, j));
#else
        for (j = 0; j < n; j++) scanf("%lf", &A(i, j));
#endif
#ifndef _WIN32
    scanf_s("%*[^\n] ");
#else
    scanf("%*[^\n] ");
#endif

    /* Print matrix A using nag_gen_real_mat_print (x04cac)
     * Print real general matrix (easy-to-use)
     */
}

```

```

nag_gen_real_mat_print (order, Nag_GeneralMatrix, Nag_NonUnitDiag,
                       n, n, a, pda, "A", NULL, &fail);
if (fail.code != NE_NOERROR) {
    printf("Error from nag_gen_real_mat_print (x04cac)\n%s\n", fail.message);
    exit_status = 2;
    goto END;
}

/* Find absolute condition number estimate of f(A) for a real matrix A using
 * nag_matop_real_gen_matrix_cond_num (f01jbc)
 * which uses numerical differentiation.
 */
nag_matop_real_gen_matrix_cond_num (n, a, pda, f, &comm, &iflag,
                                    &conda, &norma, &normfa, &fail);
if (fail.code != NE_NOERROR) {
    printf("Error from nag_matop_real_gen_matrix_cond_num (f01jbc)\n%s\n",
           fail.message);
    exit_status = 1;
    goto END;
}

/* Print absolute condition number estimate */
printf("\nf(A) = cos(2A)\n");
printf("Estimated absolute condition number is: %7.2f\n", conda);

/* nag_machine_precision (x02ajc) The machine precision */
eps = nag_machine_precision;

/* Find relative condition number estimate */
if ( normfa>eps) {
    cond_rel = conda * norma/normfa;
    printf("Estimated relative condition number is: %7.2f\n", cond_rel);
}
else {
    printf("The estimated norm of f(A) is effectively zero");
    printf("and so the relative condition number is undefined.\n");
}

END:
NAG_FREE(a);
return exit_status;
}

static void NAG_CALL f(Integer *iflag, Integer nz, const Complex z[],
                      Complex fz[], Nag_Comm *comm)
{
    /* Scalars */
    Integer j;
#pragma omp master
    if (comm->user[0] == -1.0)
    {
        printf("(User-supplied callback f, first invocation.)\n");
        comm->user[0] = 0.0;
    }
    for (j = 0; j < nz; j++) {
        /*Complex representation of cos 2z */
        fz[j].re = cos(2.0*z[j].re)*cosh(2.0*z[j].im);
        fz[j].im = -sin(2.0*z[j].re)*sinh(2.0*z[j].im);
    }
    /* Set iflag nonzero to terminate execution for any reason. */
    *iflag = 0;
}

```

10.2 Program Data

```
nag_matop_real_gen_matrix_cond_num (f01jbc) Example Program Data
4                               :Value of n
-1.0   -1.0   -2.0    1.0
 0.0    1.0   -1.0    0.0
-1.0   -2.0    1.0   -1.0
 0.0   -1.0    0.0   -1.0  :End of matrix a
```

10.3 Program Results

```
nag_matop_real_gen_matrix_cond_num (f01jbc) Example Program Results
```

A	1	2	3	4
1	-1.0000	-1.0000	-2.0000	1.0000
2	0.0000	1.0000	-1.0000	0.0000
3	-1.0000	-2.0000	1.0000	-1.0000
4	0.0000	-1.0000	0.0000	-1.0000

(User-supplied callback f, first invocation.)

```
f(A) = cos(2A)
Estimated absolute condition number is:      4.10
Estimated relative condition number is:     14.48
```
